



Bluefin Led Underwater lights.

P12 Single and Dual Colour Installation manual.

Thank you for choosing Bluefin LED underwater lights, our products have been designed and tested rigorously to ensure optimum performance and longevity.

All Bluefin Led lights are water tested so please be aware there may be moisture present on the light.

If you have ordered the Aluminium (A)option please be aware that these have been **Hard PTFE Anodised** to form a corrosion resistant coating. Please take care not to damage this coating when installing the light.

Please ensure that your product is installed as per our instructions below, failure to do so may invalidate your warranty.

Specs: electrical/fuse ratings

	Voltage	Current	Fuse rating	
P12/P12 DUAL COLOUR	12/24v	12v4.6amp 24v2amp	8amp	
	only			

Warnings:

- Do not attempt to install the lights whilst the boat is in the water.
- Ensure that the correct voltage is used for the light.
- Ensure that an in line fuse is installed with the correct fuse rating per the light installed.
- Ensure that you use the Screws provided (failure to do so will invalidate your warranty).





- Ensure all connections are made watertight.
- Do not remove the Inline Moisture Guard.
- Do not hold the light by the cable.
- Do not use abrasives on the lenses.
- Do not look directly into the light at close proximity.

Tools required for installation:

- 2.5mm(3/32") drill bit
- 15mm(19/32") drill bit
- Drill
- Posi head hand screwdriver
- Marine sealant 3M 4200 or equivalent

Installation:

Before installation please ensure the red line is horizontal (the label is fitted to the face of the light), this is to ensure you install the light perpendicular to the water line. Ensure that <u>all</u> lights are fitted the same. If the lights are not all orientated the same way the light will not appear even (different angles) in the water (see fig 5)

For optimum affect effect the light should be positioned between 8-12" (200-300mm) below the water line and at a 90 deg angle. Recommended spacing from 1-8"(0.5mtr) to 3-11" (1.2mtrs) between the lights.

Drill a 15mm (19/32") hole for the cable access through the hull, ensuring that there are no obstructions internally in the hull.

Drill 2.5mm (3/32")pilot holes to match the mounting holes on the light. (Within the packaging there is a mounting template for drilling these holes)

Key the area to where the light is to be mounted with abrasive sand paper to ensure there is a clean area for the marine sealant to bond to.

Apply marine sealant to the rear of the light on the circumference of the light and around the base of the cable gland to ensure a complete continuous bead of sealant is applied in both areas. (see fig 1)

Feed the cable through the hole and mount the light to the hull using the screws provided.

Wipe off any excess sealant and ensure the light is seated correctly without any gaps in the sealant. (It is good practice to have excess marine sealant to clean off as this will help assure a water tight seal to the hull)

Electrical connection:

Only attach the light cable to a waterproof connection or junction box, the cable must have a watertight connection otherwise your **warranty will be void**.

You will notice an inline moisture guard attached to your cable (Fig 1). If this guard is removed your warranty will be void.

Care should be taken when planning your electrical feeds/cables to the lights so as to ensure voltage drop between the batteries or power supply is minimised, on 12V systems this is especially important as the lower system voltage means a high current requirement which in turn means the potential for more voltage drop in the cable runs & connections.

If the cable gauge & connections are not sufficient for the lighting load attached you may experience incorrect operation of the lights & intermittent illumination as the supply dips below specification.

Please see the wire gauge guide attached to the instruction manual.

For help with calculations always consult with a qualified professional or contact Bluefin LED directly.

Attach the light cable to the VDC power on the boat ensuring that you use the in line fuse supplied connected to the positive(red) wire, ensure that you use the heat shrink provided to create a water tight fit into the fuse holder. (see fig 3)

P12 Dual Colour Only

When installing P12 Dual Colour lights it is advised to wire the lights up to a single switch so that all of the lights operate in sequence with each other. It is also advised that you choose an appropriate switch that has the correct power rating for the amount of lights being installed (please see the P12 Dual Colour current values above).

Fig 1



Fig 2(P12)





Fig 3



Test the light before installation ensuring that you use the correct voltage and the light is illuminated correctly.

After installation ensure again that the light is illuminated correctly before the boat goes back into the water and the lens label is removed.

After you boat goes back into the water check internally for water ingress around where the light is installed.

P12 Dual Colour Operation

- 1. When first turned on the light will start up in Dual Blue/White mode, if you turn the light off and on again quickly it will then go to Blue mode. If you turn the light off and on again quickly it will then go to White mode. If you turn the light off and on again quickly it will go to Dual Blue/White Strobe mode.
- 2. When the light is turned off for more than 5 secs it will return to standard mode.
- 3. The light output will adjust itself dependent on the surrounding temperature conditions.

P12 Single colour Operation.

- 1. When powered up for the first time or from reset, the light will appear in the standard on mode. When turned off and on again quickly it will then go to strobe mode.
- 2. Switch off the light and leave for over 5 seconds, when the light is switched back on the light will reset back in the standard mode.

The light has internal indicator LED's for fault finding, these are as follows:

- Over voltage will flash red.(check the voltage to the light)
- Under voltage will show a constant red. (check the voltage to the light)
- Over temperature will show amber.(allow the light to cool down and check if submerged)

Note: The light is designed to allow water into the outer cavity to assist cooling (Fig 4 below), this is a design feature and water will not pass this area into the light.

Fig 5

Fig 5

Ensure Red line is Horizontal to the waterline on all lights.

Maintenance:

Regularly check the installation for water ingress.

Only clean the light with a soft bristle brush.

Warranty:

Your product has a 2 year limited warranty for defects.

For any warranty issues please contact your point of sale retailer or go to www.bluefinled.com for further advice.

Installer please ensure that the SERIAL NUMBERS of the lights are written below and the manual is handed over to the end user.

Please make a note of the serial numbers of the lights here. SERIAL NUMBERS

Bluefin LED Underwater lights. YOU MUST INSTALL THIS GEL CONNECTOR OR YOUR WARRANTY WILL BE VOID!!!

Thank you for choosing Bluefin LED underwater lights, our products have been designed and tested rigorously to ensure the optimum performance and longevity.

Please ensure that your product is installed as per our instructions below, failure to do so WILL INVALIDATE YOUR WARRANTY.

Use these instructions in conjunction with the light instructions to ensure that all is fitted correctly.

Warnings:

• Do not attempt to install the lights whilst the boat is in the water.

Installation:

Fig 1 showing how the Gel connector is wired up.

Fig 2 showing how the finished Gel connector should look when finished.

Ensure that the black outer sheath is inside the gel connector.

The IP68 GEL CONNECTOR MUST BE INSTALLED OR YOU WARRANTY WILL BE VOID.




Fig 2



Bluefin LED

Cottage Farm, Cottage Lane, Norton Juxta Twycross, Atherstone. CV9 3QH

Sales - Tel: 07950 909048 simon.steadman@bluefinled.com Service - Tel: 01827 880450 Email: mark.branson@bluefinled.com Administration - Tel: 01827 880450 Email: samantha.barrie@bluefinled.com
Registered Address: Square Rig Limited, t/a Bluefin Led, Cottage Farm, Cottage Lane, Norton Juxta Twycross, Atherstone, CV9 3QH

Company Registration Number: 08871451 VAT Number: 179 2690 64





	10% V Dro	Power	Critical (P	Single co	20ft	30ft	50ft	65ft	80ft	100ft	130ft	165ft	200ft													
Circuit Type	b Low-		series	lour)	6m	9m	15m	20m	24m	30m	40m	50m	61m													
Туре	3% V Dr	Power/Cri	& GW Pl	change	6ft	10ft	15ft	20ft	25ft	30ft	40ft	50ft	60ft	70ft	80ft	90ft	100ft	110ft	120ft	130ft						
	op High-	itical (H, S	us colour	Series)	2m	3m	5m	6m	8m	9m	12m	15m	18m	21m	24m	27m	30m	34m	37m	40m						
Wire Gau		7	70				AWG	14AWG	12010/2	T W W Z T		10AWG			8AWG						To use for	then the	Then at th			
ige sele		_	_		-					060					A30	C A			OSA		r Bluefir	cable dis	າe point			
XION guia		10	70T											OAVAO		2!	30m 34m 34m 6AWG 6mm CSA 2AWG CSA 40mm CSA 2AWG CSA 1AWG CSA 210 AWG 21	the Colun								
e using i		_	_								0mm		16mm	CSA		25mm	CSA	2	0mm	CSA	mater l	in one	n & row			
Wire Gauge selection guide using information from ABYC E-11 & US Coast Guard guidelines for marine electrical installations Current flow in Amps	15A			15/		15,						Ž			1					_	_		ights sel	direction	crosses	
									0mm	CSA	6mm	CSA		USU	COA			067			ect the	າ i.e. fro	read the			
n ABYC E		20,				2AWG	[OAWG						47440			VAVA			1AWG		appropri	m panel	cable s			
Cu		>	1	\		CSA	6mm	10mm	CSA	16mm	CSA	25mm	CSA		40mm	CSA		70	(2)	S	iate cun	or batt	uggestio			
Current 1	/) 	72		12AWG	10AWG	8AWG		6AWG		ANNIG	47.44.0		2AWG		1000	TAVAO		0AWG		ent Colu	eries to t				
low ir		>	1		4mm	6mm	10mm	CSA	16mm	CSA	25mm	CSA	1000	430	COA		70mm	CSA			ım for yo	he light	or EU ga			
nt flow in Amps)	9		10000	TOW WO	8AWG	SWV9	OH WY	ANNE	TAV VV	SWAC	24447	1AWG		0AWG			MVV 010	VIORAN	u lights, p	placeme	uges for			
STorman	Drop Low- Or None None Power/Critical (H, S all (P series)) Series Colour) Series Se	CSA		70mm	CSA			,		power &	nt or gro	your inst														
ne electric		_	-		OWYO	OAWG	CAMP	DAVVO	AMM	- TAVA	2////С	CANAC	1AWG	OVWG	OAVVO	2000	CINAMOIS		310AWG		quantity	up.	allation.			
al Instai		>	Ì		10mm	CSA	16mm	CSA	25mm	CSA	40mm	CSA	7000	087	COA						from the					
lations		<u>.</u>	Ų			6AWG		SWW	7444	3/1/1/6	0.44 27	1AWG	0AWG	olo vwc	2 O AVV	7VV 016	SIOAWO		4 0 AW(top row					
		>	Ä		16mm	CSA	25mm	CSA		CS 1	COA	70mm	CSA	1)		IJ			(0)							
		n	0		CVIVO	DAVVO		4AVVO	2000	24447	1AWG	0AWG	2 0AWG	MV 018	SICHARO		4 0AW									
		>	A		25mm					70mm			G	וו			G									